



ORDERING INFORMATION

Model	Description
CHU-600	PowerLine USB Adaptor

CHU-600, PowerLine USB Adapter

The PowerLine USB Adapter links your USB-equipped computers and devices over your existing standard electrical wiring. CHU-600 eliminates the need to run cabling between them. Simply plug one end of the adapter into an available wall outlet and connect the other end to any available USB port. The Adapter sets up on any laptop or desktop with the simplicity of Plug-and-Play technology. You can easily network anywhere in your home or office without complicated cabling.

FEATURES and BENEFITS:

- Plug-&-Play Operation Provides Easy Setup
- Uses Existing AC Wires for Instant Connectivity Anywhere with an Outlet
- Built-in QoS and Error Correction Features
- Plugs Directly into Outlet, Uses no Desk Space
- Compatible with Other HomePlug-compliant Products

SPECIFICATIONS

Model	CHU-600
Standards	<ul style="list-style-type: none">• HomePlug 1.0 compliant• USB 1.1 compliant
Data Speed	<ul style="list-style-type: none">• Up to 12Mbps
Encryption	<ul style="list-style-type: none">• 56-bit DES Link Encryption
Interface	<ul style="list-style-type: none">• One power line interface• One USB type B jack for host computer connection
Environment	<ul style="list-style-type: none">• Operating Temperature: -20° ~ 70°C (-4° ~ 158°F)• Storage Temperature: -40° ~ 80°C (-40° ~ 176°F)• Humidity: 10% ~ 90% Non-condensing
Certifications	<ul style="list-style-type: none">• CE, FCC
Dimensions (L x W x H)	<ul style="list-style-type: none">• 93 x 57 x 42mm (3.68 x 2.24 x 1.65 inches)
Software Support	<ul style="list-style-type: none">• MS Windows 98SE/ME/2000/XP

ORDERING INFORMATION

Model	Description
CHU-600	PowerLine USB Adaptor